



Integrated all-in-one multiroom system, complete with amplification and multimedia audio sources compatible with KNX, MQTT, REST.API and home automation third. Management and supervision via Telemaco APP available for iOS & Android. System expandable to 6 players to 12 zones, combining 2 Telemaco.

Inputs:

- 3 stereo inputs unbalanced line level 0db
- Power supply connector
- Micro SD

Outputs:

- 6 amplified outputs (6x20W @ 4ohm)
- 6 line level balanced preamp outputs to expand the number of speakers or power zone via external amplifiers (##Vivaldi Multimedia E30S#, ##Vivaldi Multimedia E80S#, Vivaldi PMA , Vivaldi PSA series power amplifiers, Vivaldi active subwoofers, Vivaldi active speakers)
- 8 Ohm speakers for each output, minimum impedance 4 Ohm

Connectivity:

- KNX connector embedded
- RJ45 LAN 10/100 connector

Player / Users:

4 Players integrated with services

Spotify Connect
Webradio
Airplay
NAS
Local music (Android)
Playlist
AUX

Other:

- Playlist creation and quick access
- Favorite webradio with fast access
- Preset functionality with quick access
- Function Doorbell with choice for single zone do not disturb
- Webpage configuration
- Customizing Player/User names, AUX inputs and zone outputs
- Shortcut access to player/user
- Stereo zone setting (for up to 3 stereo zones or mono/stereo combination)
- Possibility to pair two devices to create a single 12-zones system, 6 AUX inputs, 6 players (maximum 6 stereo zones or mono/stereo combinations)
- Dedicated control app (Vivaldi Telemaco)
- Supported control APIs: KNX, MQTT, REST (with access token)
- Multi-function touch button on the front (DHCP reset, factory reset, static IP...)
- Multi-colored LED status bar.
- Energy saving amplifiers
- OTA updates

Option:

[Vivaldi Multimedia C4IO](#) programmable buttons with 4 inputs. Short or long press multifunction keys to associate two functions to each single Button. The first two inputs (buttons) can be used with rotary encoder ([Vivaldi Multimedia TVE](#) to be ordered separately) for volume control.

Functions assignable to the buttons [Vivaldi Multimedia C4IO](#):

Increase / decrease in volume
Inputs / outputs
Mute and deactivation switch
Preset recall
Forward/backward track player
Stop
Play / Pause player
Play USB (priority)

Cables to be used:

- #Vivaldi Ulisse MICRO2.50## system cable for analog inputs and preout outputs
- Red-black cable 2x0,75 or equivalent for speaker connection and power supply
- LAN cable cat5e/cat6
- KNX bus cable

VIVALDI

Dimensions (WxHxD): 106x91x62mm, 6 DIN modules.

Weight: 0,250 kg

Power supply : 24vdc / 150W max (#Vivaldi Giove AL6B## not supplied)

Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice



Images

Vivaldi Multimedia TELEMACO



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA

Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it

P.IVA e C.F. 02880360272

VIVALDI



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it
P.IVA e C.F. 02880360272