



DSP stereo amplifier.

D - class power ampl 30+30W @ 80hm, 50+50 @ 40hm.

Balance stereo input.

Amplifier output customisable as below:

- Linear stereo with volume adjustment for single channel, internal with trimmer or external with potentiometers (mono [Vivaldi Giove TVM](#), stereo [Vivaldi Giove TVS](#));
- Subwoofer mode with cut frequency adjustment and trimmer volume.
- Balance stereo line output for active subwoofer connection or auxiliar amp [Vivaldi MULTIMEDIA E30S](#), ##Vivaldi MULTIMEDIA E80S##;
- Possibility to select if linked to the master volume or fixed.
- The device can be set in stereo or mono mode by the dip swich on board.

Power supply 24Vdc via [Vivaldi Giove AL5B](#) (not included)

Standard DIN (6 modules)

Size (WxHxD): 106x90x63 mm

Weight 0.14 kg.

*Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice*

# VIVALDI

 Images

## Vivaldi MULTIMEDIA E30S



**Vivaldi** srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA  
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it  
P.IVA e C.F. 02880360272