



Multimedia stereo device with DSP and multimedia player embedded for WebRadio, Spotify ecc....

Matrix 6 inputs + 1 source.

VIVALDI supervision and control APP (downloadable from iOS & Android).

API available:

-KNXnet-IP (KNX IP mandatory Router is not provided)

-Protocollo MQTT 3.1 (through external Broker or integrated)

-REST-API (HTTP GET/POST)

6x SELECTABLE MIC/LINE INPUTS with activable Phantom (24Vdc), assignable priority (can be activated with contact).

USB Type A on the front for MP3/WMA/AAC/AAC+/ALAC/FLAC/APE/WAV audio file playback.

3-band equalizer.

Outputs for power expansions [Vivaldi MULTIMEDIA E30S](#), [Vivaldi MULTIMEDIA E80S](#) or power amps Vivaldi Ulisse Line at 8Ω or 100V.

1x RJ45 per LAN.

1x PATCH cable 1mt.

Audio parameter control with volume/settings/... from webpage. Can be integrated with home automation systems [Vivaldi Domotica iCONTROL4.1L](#), [Vivaldi Domotica iCONTROL4.0+](#) via LAN.

Power Supply 24Vdc via [Vivaldi Giove AL2B](#) (not included).

DIN standard (6 modules).

Dimensions (WxHxD): 106x90x63 mm.





Weight 0.2 Kg.

VIVALDI

Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice

Images


Vivaldi Multimedia MATRIX6



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it
P.IVA e C.F. 02880360272

VIVALDI



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it
P.IVA e C.F. 02880360272

VIVALDI



Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it
P.IVA e C.F. 02880360272